



The Escort is a versatile exit sign, featuring an all-in-one design that uses the same compact housing for both AC, AC/DC and Self-Powered models. The signs are molded in tough high impact thermoplastic with a scratch resistant suede finish. Its off white or optional black color blends well with a variety of interiors and matches other Escort family emergency units and remote heads.

Evaluated to UL 924 Standard

Light Sources

- LED, Light Emitting Diodes, red LED's of ALINGAP technology

Sealed Maintenance-Free Batteries

- Nickel-Cadmium

Standard Features

Reliability

The **EC Escort Thermoplastic LED Exit Series** has a 5-year full warranty.

Unit Data

Exit frame, backplate, faceplate and mounting canopy is constructed of rugged high impact off white thermoplastic.

LED Light Source

- Models consume less than 2.2 watts
- Even illumination, without hot spots.
- All self powered units come complete with test switch and AC on indicator.
- Available with damp location listing.

High Performance Current Regulated Circuitry

- Uniform LED light output
- Battery is sealed, maintenance-free Nickel-Cadmium for superior performance and long life.
- No canopy is required for back mounted signs.
- Test switch and pilot light is located on side of sign.
- Provide 90 minutes of emergency operation as per UL 924.
- Universal voltage, 2-wire input: 120-277Vac 50/60 Hz.

Power Consumption

Model	AC Specs		DC Specs	
AC-only	120 to 277 Vac	1.6 W	-	-
AC/DC	120 to 277 Vac	1.6 W	6 to 24 VDC	Less than 1.5 W
Self-powered	120 to 277 Vac	2.2 W	NiCad battery	Min. 90 minutes

How To Order (example)

Housing	ECLXN	4	R	-VR1
Blank=white B=black	Series ECL= AC-Only ECLXN= Self-powered Nickel-Cadmium battery	Face 4=Universal 2 faces, backplate and canopy	Stencil Face R=red G=green Open face* RW=red on white GW=green on white	Option See Option chart

*Open face required only with special wording.

Diagnostic / Self Test (Optional)

Self-Powered units with the diagnostic / self test option have a test switch, external AC on and "Service Required" indicators. The diagnostic / self test option features continuous monitoring of the charger assembly, battery and LED assembly current. If a fault is indicated the external service required indicator will illuminate. The internal fault indicators will then indicate the nature of the fault. The diagnostic / self test option will also self test 30 seconds every 30 days, 30 minutes every 60 days and 90 minutes annually.

Optional Features

Add

Suffix AC/DC Remote (6-24Vdc)-DC
Fire alarm activated flasher (AC-only sign)-FAF
Dual AC circuit (120/120 or 277/277)-2CKT*
Damp location-DL
Diagnostic / self test (self-powered)-D
Fire alarm activated flasher (self-powered)-FA
Flasher / buzzer (self-powered)-FZ
Vandal resistant screws-VR
Vandal resistant shield and screws-VR1

*AC-only units

Accessories (order as a separate item)

White pendantP*-WT
Black pendantP*-BK
Wire Guard (wall mount)WG1-E
Wire Guard (ceiling or end mount)WG5-E

*Specify pendant length (12", 24", 36", etc)

Outline and Dimensions

Dimensions are approximate and subject to change.

