



ACX SERIES BATTERY CHARGERS

For SLA Batteries

OPERATING CHARACTERISTICS

“ACX” series chargers are new “switching” type devices which operate without the use of transformers. I.C.’s control and regulate current and voltage and automatically switch from the higher fast charge voltage to the lower float voltage when batteries are very close to being fully charged. At the float voltage it is safe to leave the battery connected to the charger indefinitely, making charging pretty much fool-proof.

In the fast charge mode voltage goes up to 2.45V +/- 0.05V before switching, in the float charge mode voltage is held between 2.25- 2.30V/cell.

This charger is ideal for cyclic applications where recharge time is critical and timely charge termination cannot be counted on. This charger ensures optimum battery performance & service life.



Intertek

SPECIFICATIONS

Model	Nominal Voltage	Output Voltage Float/Fast Charge	Output Current mA	Type Automatic	Dimensions: inch (mm)			Weight		Charging Capacity Range
					Length	Width	Height	lbs.	kgs.	
PSC-6500ACX	6	6.7 / 7.35	500	dual rate	3.15 (80)	2.24 (57)	1.97 (50)	0.21	0.10	2Ah to 5Ah
PSC-61000ACX	6	6.7 / 7.35	1000	dual rate	3.15 (80)	2.24 (57)	1.97 (50)	0.20	0.09	5Ah to 12Ah
PSC-12500ACX	12	13.3 / 14.70	500	dual rate	3.15 (80)	2.24 (57)	1.97 (50)	0.20	0.09	2Ah to 5Ah
PSC-121000ACX	12	13.3 / 14.70	1000	dual rate	3.15 (80)	2.24 (57)	1.97 (50)	0.20	0.09	5Ah to 12Ah
PSC-124000ACX	12	13.7 / 14.70	4000	dual rate	5.43 (138)	2.83 (72)	1.65 (42)	0.95	0.43	14Ah to 55Ah

GLOBAL HEADQUARTERS
(USA AND INTERNATIONAL EXCLUDING EMEA)
Power-Sonic Corporation
365 Cabela Dr Suite 300,
Reno, Nevada 89523
USA
T: +1 619 661 2020
E: customer-service@power-sonic.com

POWER-SONIC EMEA
(EMEA – EUROPE, MIDDLE EAST AND AFRICA)
Smitspol 4, 3861 RS Nijkerk,
The Netherlands
T NL: + 31 33 7410 700
T UK: + 44 1268 560 686
T FR: + 33 344 32 18 17
E: salesEMEA@power-sonic.com

FEATURES

- Universal input voltage range 100VAC - 240VAC
- Automatic, current sensing dual-rate charging for efficient, care-free and safe operation
- LED indicators
- Alligator clip connectors with insulated sleeves

APPROVALS

- ISO9001:2015 – Quality management systems
- DOE compliant
- CE compliant
- FCC compliant
- ETL approved
- Approved for transport by air. D.O.T., I.A.T.A., F.A.A. and C.A.B. certified

CALCULATING RECHARGE TIME

Recharge time depends on the depth of the preceding discharge and the output current of the charger. To determine the approximate recharge time of a fully discharged battery, divide the battery’s amp. hrs. by the rated output current of the charger and multiply the resulting number of hours by a factor of 1.75 to compensate for the declining output current during the charge cycle. If the amount of amp. hrs. discharged from the battery is known, use it instead of the battery’s capacity to make the calculation.

To ensure safe and efficient operation always refer to our Charger Operating Instructions, as published on our website.

FURTHER INFORMATION

Power Sonic offers a wide range of chargers suitable for batteries with a variety of capacities. If you have any queries or need help choosing a charger please contact our technical team who will be happy to help.