

Thermoplastic ELX-MRS Series EXCO





Outline and Dimensions





141/4"

Combination exit and emergency light

How To Order (example)

ELXN400	R	2MRS	В
Series	Stencil Face	Light Heads**	Colour
ELX400 = AC-Only	$\mathbf{R} = Red$	2MRS = 2 MR16 lamps	$\mathbf{B} = Black$
ELXN400 = Self-powered*	$\mathbf{G} = \text{Green}$	6V 5W	

^{*} Combo units only available as self-powered.

The **ELX-MRS Series** is perfect for use where style and design is required in an economical package. Long Life LED's are used in all exit sign models. NiCad batteries are utilized in the self-powered exit Signs. The combo units six volt, MR16, lamps are powered by a maintenance-free, Lead-Calcium battery to provide a clean, adequate amount of light. The snap-together thermoplastic housing facilitates quick assembly making the ELX-MRS the most affordable sign on the market.

UL Listed

Complies with NEC, Life Safety Code and OSHA. Damp location listing is standard on all models.

Light Source (exit)

LED, Light Emitting Diodes, red LED's of ALINGAP technology

Sealed maintenance-free batteries

Lead-Calcium
Nickel-Cadmium

Standard Features

- · Rugged thermoplastic construction
- Even illumination for excellent legibility.
- Snap-together design for quick and easy installation
- Universal mounting, complete with 2 faces, backplate, and canopy
- Replaceable knockout directional chevrons
- Energy efficient, long-life LED's (red or green)
- · Listed to UL Standard 924

Emergency Models (exits)

- Replaceable, sealed Nickel-Cadmium battery
- Provides a minimum 90 minutes of continuous emergency illumination
- · Energy star compliant
- Batteries recharge per UL924 specifications
- All exit sign models consume less than 5 watts

Emergency Models (combination units)

- · 6 volt, sealed, maintenance-free Lead-Calcium battery
- Fully adjustable, glare-free, 6 volt MR16 lamps

Charger

- 120/277VAC input
- Temperature compensated
- Short circuit protected
- Push to test switch
- Fully automatic charger
- Brown out protection
- · Low voltage battery disconnect
- AC pilot light

ELX-MR Series Offers Three Models

AC-only exit signs, red or green Self-powered exit signs, red or green Self-powered combo units, red or green

Accessories (order as a separate item)

TIOUS (STADE AS A SUPERIOR HOLD)	
Description	Add Suffix
Replacement MR16 lamp, 6V 5W	580.0072
Wire Guard (exit only)	
Wall mount	WG1
Ceiling or end mount	WG5
Wire Guard (combo)	
Wall mount	WG6

@2008. Thomas & Betts Ltd. All rights reserved. Printed in Canada. 06/08/1200. Order no. EL/ELX-MRS CATSHEET

EMERGI-LITE Exit Series

^{**} Light heads only applicable to combo units.