# Preceptor™ Remote Capacity Series

Die-cast aluminum remote capacity exit sign



# Construction

- Die-cast aluminum housing
- Panel features a curved contour for maximum illumination and clarity
- 6 inch EXIT lettering legend available in red or green
- Field-selectable chevrons
- Choice of finishes: white, black or brushed aluminum

#### Mounting

- Surface mount
- · Canopy included for end or ceiling mount applications
- Universal J-box mounting

## Electronics

- Optional Advanced Diagnostics
- 120/277 60Hz

## **Choice of battery**

• RCL model, (lead-calcium battery) 6V-9W remote load capacity

- RCN model, (nickel-metal hydride battery) 6V-12W remote load capacity
- RCX model, (nickel-metal hydride battery) 6V-24W remote load capacity

#### Special wording panels

· Available. Contact your sales representative with your design requirements

## Approvals

- UL 924 listed
- Damp location optional (50°F to 104°F)
- Meets NFPA101 (Life Safety Code), NFPA 70 NEC, OSHA illumination standards

## Warranty

· Unit has a five-year limited warranty Detailed warranty terms located on page 178 or online at: www.emergi-lite.com/usa/files/EL\_Warranty.pdf

**Power consumption** 

		AC specs					Battery capacity in watts	
Series	AC input	Maximum	Voltage	Battery	1-1/2 hrs	2 hrs	3 hrs	4 hrs
RCL			6V	Lead-calcium	9	-	_	_
RCN	120/277VAC, 60Hz	0.13/0.06A 15W	6V	NiMH	12	9	_	_
RCX	-		6V	NiMH	24	18	12	9

#### Housing color



White




COMMERCIAL


#### Dimensions

Dimensions are approximate and subject to change.


# **Ceiling mount**



# Back mount



#### End mount



#### Accessories (order as a separate item)

Description	Suffix
Wire guard, back mount	WG13-E
Wire guard, ceiling mount	WG14-E

#### How to order

Housing color	Series	Battery type	# of faces	Legend color	Options
BA= Black body/	P= Preceptor	RCL= Sealed	1= Single face	R= Red	AD= Advanced Diagnostics (audible)
aluminum face		lead-calcium,	2= Double face	<b>G</b> = Green	ADNA= Advanced Diagnostics
BB= Black body/		9W remote		<b>RW</b> = Red on white	(non-audible)
black face		capacity		(Open face required	D3= Time delay (15 minutes)
<b>WW</b> = White body/		RCN= Sealed		for special wording)	DL= Damp location
white face		nickel-metal		<b>GW</b> = Green on white	FA= Fire alarm activated flasher
<b>WA</b> = White body/		hydride,		(Open face required	FZ= Flasher buzzer
aluminum face		12W remote		for special wording)	VR= Vandal-resist screws
AA= Brushed aluminum		capacity			VR1= Vandal-resistant polycarbonate
body and face		RCX= Sealed			lens and screws
-		nickel-metal			
		hydride, 24W			
Example: BAPRCL2R		remote capacity	1		