

SPECIFICATION SHEET : SC-230-287-CUV

This Is An Original Product From Fulham Co., Inc


Description : PONY Series, High Frequency Electronic, Rapid Start Ballast, * Meets Energy Star 4.0 Criteria For Applications Listed.

This Ballast Will Operate Following Lamps.

8 ┮₽

180mm T5 UV / 287mm T5 UV

INPUT VOLT: 230V ± 10%, 50/60Hz										
LAMP WATTS/TYPE	180mm T5 UV	287mm T5 UV	-	-	-		-	-	-	
LAMPS OPERATED	1	1								
INPUT WATTS	11.40	15.77								
LINE CURRENT:	0.096	0.136								
POWER FACTOR	0.522	0.501								
BALLAST FACTOR	0.842	0.939								
EFFICACY FACTOR	7.390	5.950								
THD	157.70	165.60								
CURRENT CREST FACTOR	< 1.7									
EMI/RFI COMPLIANCE	FCC PART 18-A									
SOUND RATING	"A"									
BALLAST TYPE	RAPID START									
VOLTAGE TRANSIENTS	ANSI 62.41									
INPUT/PROTECTION	FUSE									
OUTPUT/PROTECTION	EOL									
MIN. OPERATING TEMP	0 [°] C (32 [°] F)									
MAX. CASE TEMP	75 ⁰ C(167 ⁰ F)									
APPROVALS/CLASS	UL LISTED, CLASS " P ", 1 OUTDOOR									



WIRING DIAGRAMS												
MRE	BLACK	WHITE	RED	BLUE	YELLOW	BROWN						
ENGTH - INCHES	12 <u>+</u> 1"	12 <u>+</u> 1"	8 <u>+</u> 1"	8 <u>+</u> 1"								
Г												
	POWER SIDE		LAMP SIDE	BLUE - BLUE - BLUE - RED								
L				RED	1							
1	80mm T5 UV / 2	287mm T5 UV	Г									
			B									

Fulham Co., Inc extends limited warranty only to the original purchaser or to the first user for the period of 2 years from the date of manufacture as indicated by the date code stamped on each product and when properly installed and under normal conditions of use. For additional warranty guide line, please refer to our Complete Product Catalog OR call Customer Service at 1-599-5000

DUE TO A PROGRAM OF CONTINUOUS IMPROVEMENT, FULHAM Co., INC RESERVES THE RIGHT TO MAKE ANY VARIATION IN DESIGN OR CONSTRUCTION TO THE EQUIPMENT DESCRIBED. Address : 12705 South Van Ness Ave., Hawthorne, CA 90250 Tel.: 1-599-5000, Fax.: 1-323-754-9060. Website: www.fulham.com

ELECTRICAL DATA