


SPECIFICATION SHEET : WHAM-120-213-L

This Is An Original Product From Fulham Co., Inc

Description : WorkHorse Series Fluorescent T5 Electronic Ballast - All The Features Of WorkHorse, Thin Undercabinet Applications.


This Ballast Will Operate Following Lamps.



ELECTRICAL DATA

INPUT VOLT: 120V ± 10%, 50/60Hz									
LAMP WATTS/TYPE	F28T5	F14T5	F21T5				-	-	-
LAMPS OPERATED	1	1	1						
INPUT WATTS	26	17	21						
LINE CURRENT:	0.23	0.15	0.20						
POWER FACTOR	0.96	0.94	0.95						
BALLAST FACTOR	0.9	1.0	1.0						
EFFICACY FACTOR	3.5	6.1	4.9						
THD	28%	33%	30%						
CURRENT CREST FACTOR									
EMI/RFI COMPLIANCE	FCC PART 18-A (Non-Consumer)								
SOUND RATING	" A "								
BALLAST TYPE	RAPID START								
VOLTAGE TRANSIENTS	ANSI 62.41								
INPUT/PROTECTION	FUSE								
OUTPUT/PROTECTION	-								
MIN. OPERATING TEMP	0 °C (32 °F)								
MAX. CASE TEMP	75 °C (167 °F)								
ENERGY STAR 4.0	YES								
APPROVALS/CLASS	CLASS " P ", 1 OUTDOOR								


MECHANICAL DATA



Where : L = Length, W = Width, H = Height

WIRING DIAGRAMS

WIRE	BLACK	WHITE	RED	BLUE	YELLOW	BROWN
LENGTH - INCHES	12 ± 1"	12 ± 1"	24 ± 1"	-	24 ± 1"	-



NOTE : This Ballast Case Must Be Grounded

Fulham Co., Inc extends limited warranty only to the original purchaser or to the first user for the period of 3 years from the date of manufacture as indicated by the date code stamped on each product and when properly installed and under normal conditions of use. For additional warranty guide line, please refer to our Complete Product Catalog OR call Customer Service at 1-800-2-Fulham.

DUE TO A PROGRAM OF CONTINUOUS IMPROVEMENT, FULHAM Co., INC RESERVES THE RIGHT TO MAKE ANY VARIATION IN DESIGN OR CONSTRUCTION TO THE EQUIPMENT DESCRIBED.

Address : 12705 South Van Ness Ave., Hawthorne, CA 90250 Tel.: 1-800-2-fulham, Fax.: 1-323-754-9060. Website: www.fulham.com 2006-30SP rev C