
PS Series 6 and 12 Volt Square Shooter







Unit Rating Chart

6 volt unit furnished with 6 watt Halogen lamp(s). 12 volt unit furnished with 8 watt Halogen lamp(s).

UNIT EQUIPMENT - NO REMOTE CAPABILITY								
Sealed Maintenance-Free Battery Types	D.C. Voltage	Model Number	*Watts to 871/2% of rated battery voltage 11/2 hrs. 2 hrs. 3 hrs. 4 hrs.					
Long Life Lead + A	6	PSE9	9	7	_	-		
Lead Calcium	6	PSM9	9	6	-	ı		
UNIT EQUIPMENT - WITH REMOTE CAPABILITY								
Nickel Cadmium	6	PSC18	18	12	9	6		
	6	PSC18-2	18	12	9	6		
	6	PSC25	25	18	12	9		
	6	PSC25-2	25	18	12	9		
	12	12PSC36	36	21	15	12		
	12	12PSC36-2	36	21	15	12		
Long Life Lead + A	6	PSE18	18	11	8	6		
+ Δ	6	PSE18-2	18	11	8	6		
	6	PSE36	36	24	17	13		
	6	PSE36-2	36	24	17	13		
	12	12PSE36	36	24	17	13		
	12	12PSE36-2	36	24	17	13		

^{*}National Electrical Code Specification

-2 indicates two lamp version

 Δ = Advanced Diagnostics Available

How To Order (example)

For standard units without options only order Series, Battery, and Watts

PS C 18 Battery Type nickel cadmium for 90 min.

Includes standard lamp

Options are added to units by listing suffix at end of model #

*(HA) TD(5) Lamp Option Option 6V 6W tungsten Time delay 5 min.

*see lamp data sheet in lighting fixture section for other lamp wattages.

The **PS Series** is architecturally designed to harmonize with a variety of interiors. Units are available as surface mount, semi-recessed mount or fully recessed mount. The Square Shooter has a 172 X 172 beam distribution pattern.

UL Listed

Complies with NEC, Life Safety Code and OSHA. Approved use in the Commonwealth of Pennsylvania.

Sealed Maintenance-Free Batteries

• Nickel Cadmium • Long Life Lead • Lead Calcium

Standard Features

Reliability The PS Series comes complete with a 3-year full warranty.

Unit Data Surface mount, semi-recessed units and fully recessed kits are constructed of an off-white, impact resistant, flame retardant, polymeric material. Fully recessed, "FRM" option units have an all metal back box. All furnished standard with one halogen lamp (6 volt 6 watt or 12 volt 8 watt).


PulsePlus Charger PulsePlus circuitry offers 120/277 volt input 60 Hz., 0.3 Amp (other inputs available), fused output circuit(s), temperature compensated charger, sealed relay, low voltage battery disconnect, brownout protection and lockout (automatic battery connect).

Optional Features

Description	Add Suffix
Ammeter OR voltmeter (choose only one) not available FR mode	lsA* OR V*
PulsePlus OR advanced diagnostics (choose only one)	PPD 0R AD
Dual lamps	
Time delay (Specify 5, 10 or 15 minutes)	TD**
Non-standard input voltage	Specify
Polycarbonate lens	
Fully-recessed all metal unit	FRM***
Unit color in black	В
Accessories (order as a separate item)	
Semi-recessed kit (converts a surface mount unit to semi-recessed)	.PS-SRKIT***
Fully-recessed kit (converts a surface mount unit to fully-recessed)	.PS-FRKIT***
Wire guard (surface or semi-recessed)	WG1
Wire guard (fully-recessed)	WG11
(2) 24" adjustable bar hangers for drywall construction	BH
(2) 27" adjustable bar hangers for suspended grid ceilings	sTBH
*Not available with diagnostics options.	
**Not required when using the AD option.	
***Par hangara included	

Outline and Dimensions

Dimensions are approximate and subject to change.



^{+ =} PulsePlus Diagnostics Available

^{***}Bar hangers included.